

PA MULTI-ZONES MIXING AMPLIFIER (19" RACK/DESK-TOP MOUNTING)



MIP-120E



MIP-60E



TYPE	MULTI-ZONES MIXING AMPLIFIER	
MODEL	MIP-120E	MIP-60E
POWER SUPPLY	AC 115/230V 50/60Hz, DC 24V	
POWER OUTPUT	120W RMS	60W RMS
TOTAL HARMONIC DISTORTION	$\leq 1\%$ @ 1 KHZ	
SENSITIVITY	XLR(BALANCED) CHANNEL 1-3 (MIC 1-3) 1mV @ 600 Ω TEL (TERMINAL) 100mV @ 600 Ω CHANNEL 4 (MIC 4) 1mV @ 600 Ω AUX 1 (RCA) 100mV @ 22K Ω CHANNEL 5 (MIC 5) 100mV @ 600 Ω AUX 2 (RCA) 100mV @ 22K Ω AUX 3 (RCA) 100mV @ 22K Ω TAPE OUT(RCA), AUX OUT(RCA) 1V	
FREQUENCY RESPONSE	50 Hz - 20K Hz $\pm$ 3dB	
OUTPUT	100V, 70V, 8 Ω	
SIGNAL TO NOISE RATIO	86 dB	
PAGING ZONE CONTROL	INDIVIDUAL $\times$ 5 + MASTER $\times$ 1	
CHIME INPUT	MIC 5	
VOICE PRIORITY MUTE	MIC 1	
PHANTOM POWER ADJUSTABLE	MIC 1-5	
TONE	BASS 100Hz $\pm$ 10dB TREBLE 10KHz $\pm$ 10dB	
AC POWER CONSUMPTION	320 W @ RATED POWER	160W @ RATED POWER
DC POWER CONSUMPTION	8A @ RATED POWER	4A @ RATED POWER
DIMENSION	88mmx425mmx305mm (HWD)	
WEIGHT	9 KGS	8 KGS
MOUNTING	FREE STANDING OR 19" RACK	